



0000

A34114

2600

PATENT

2641

RS

#

2

5-30-01

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant : Robert John Haycock
Serial No. : 09/808,613
Filed : March 14, 2001
For : METHOD FOR CONTROLLING A
DATE TRANSMISSION PRE-
EMPHASIS UNIT AND A DATA
TRANSMISSION SYSTEM
EMPLOYING THE METHOD

RECEIVED

MAY 16 2001

Technology Center 2600

I hereby certify that this paper is being deposited with the United States Postal Service as first class mail in an envelope addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231

May 10, 2001

Date of Deposit

Ronald B. Hildreth

Attorney Name

19,498

PTO Reg. No.

May 10, 2001

Date of Signature

[Signature]
Signature

CLAIM FOR PRIORITY UNDER 35 U.S.C. §119

Assistant Commissioner for Patents

Washington, D.C. 20231


Sir:

A claim for priority is hereby made under the provisions of 35 U.S.C. §119 for the above-identified U.S.

patent application based upon Great Britain patent

Application No. 0005976.6 filed March 14, 2000. A certified
copy of this Great Britain application is enclosed.

Respectfully Submitted,

A large, stylized handwritten signature in black ink, which appears to read "Ronald B. Hildreth". The signature is written over a horizontal line and extends to the right, with a long, sweeping tail.

Ronald B. Hildreth

Patent Office Reg. No. 19,498

Attorney for Applicants
212-408-2544

Enclosure



RECEIVED

MAY 16 2001



Technology Center 2600

INVESTOR IN PEOPLE


The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.




Signed

Dated

15 MAR 2001

**CERTIFIED COPY OF
PRIORITY DOCUMENT**



The Patent Office

14HAR00 207572 D00107
P01/7700 0.00-0005976.6

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road

Newport

Gwent NP9 1RH

1. Your reference

N00/0067/GB

2. Patent application number

(The Patent Office will fill in this part)

0005976.6

14 MAR 2000

3. Full name, address and postcode of the or of each applicant (underline all surnames)

Power X Limited
Stafford Court
145 Washway Road, Sale
Manchester M33 7PE

Patents ADP number (if you know it)

6803233002

If the applicant is a corporate body, give the country/state of its incorporation

4. Title of the invention

Data Transmission Driver Device

5. Name of your agent (if you have one)

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

McNeight & Lawrence
Regent House, Heaton Lane
Stockport, Cheshire SK4 1BS

Patents ADP number (if you know it)

0001115001 ✓

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number
(if you know it)

Date of filing
(day / month / year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(day / month / year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if:

Yes

a) any applicant named in part 3 is not an inventor, or

b) there is an inventor who is not named as an applicant, or

c) any named applicant is a corporate body.

See note (d))

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description 10

Claim(s) 2

Abstract 1

Drawing(s) 8 *xs*

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77) 1 *✓*

Request for preliminary examination and search (Patents Form 9/77) 1 *✓*

Request for substantive examination (Patents Form 10/77)

Any other documents (please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

McNeight & Lawrence

13 March 2000

12. Name and daytime telephone number of person to contact in the United Kingdom
- J G Lawrence
0161 480 6394

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- b) Write your answers in capital letters using black ink or you may type them.
- c) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- d) If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- e) Once you have filled in the form you must remember to sign and date it.
- f) For details of the fee and ways to pay please contact the Patent Office.

DATA TRANSMISSION DRIVER DEVICE

Field of the invention

The present invention relates to a driver for data transmission, and particularly to a driver which provides frequency dependent pre-emphasis.

5 Background of the invention

The frequency response of a interconnect (e.g. a PCB/cable) used for data transmission attenuates the high frequency components of a data stream. The level of this attenuation is illustrated schematically in Fig. 1, showing that it arises at above a frequency labelled ω_2 . When the attenuation starts below the maximum frequency of the data stream, this leads to a phenomenon known as inter-symbol interference (ISI), in which certain data patterns cause thinning of the data pulse widths, and hence there is data dependant jitter. A worst case example of this is for a data pattern in which the transmitted data has a single data high amongst data lows, as shown in Fig. 2(a). The attenuation of the high frequency components of the single data high results in a pulse which has reduced amplitude and long rise/fall times. Consequently pulse widths are reduced as shown in Fig 2(b).

The CML type driver, illustrated in Fig. 3, includes a differential pair at the transmitter and loads at the receiver. The two inputs (which are equal and opposite voltage signals) are amplified by an amplifier 1, and then fed as equal and opposite signals tx_n and tx_p to respective transistors 3,5. The transmission lines 7, 9 have an impedance Z_0 . The loads R are at the termination for the transmission lines. An rx amp 10 is provided at the output. The gain of the driver is proportional to the width of the transistors 3,5 in the differential pair. Wider transistors provide more gain. A CML-type driver illustrated in Fig. 3 provides equal gain at all frequencies.

However, drivers are known which provide a pre-emphasis which flattens the frequency response of the interconnect at higher frequencies, preferably up to and beyond the data signal frequency. This is illustrated in Fig. 4, in which Fig. 4(a) is the frequency response of the interconnect, Fig.

4(b) is the frequency response of the pre-emphasis filter which has a pole at ω_2 , and Fig. 4(c) is the frequency response of the combination of the two, which is flat up to frequency ω_1 . The pre-emphasis filter has a zero at ω_2 to cancel the pulse of the interconnect. The pre-emphasis filter also has a pole at ω_1 but this is higher than the maximum data frequency. Such known drivers employ passive components to achieve the frequency response shown in Fig. 4(b). This means that, taking the pre-emphasis and data transmission period as a whole, low and high frequency components are both attenuated by the same amount, and little or no thinning of the pulse widths occurs.

Summary of the Invention

The present invention seeks to provide a new and useful driver for data transmission.

In general terms, in a first aspect the present invention proposes that in a data transmission system in which a signal which is transmitted as a difference between two currents, the signal is divided into two, and each divided signal is used to modulate a respective one of the currents. One of the signal paths includes a low pass filter, so that the difference between the two currents is greater for higher frequency components than for low frequency components.

The invention is particularly relevant for use in a system in which data is carried by two equal and opposite input signals. Preferably, each input signal is used to regulate (modulate) a current which passes along a different respective one of the lines, and, additionally, relatively low frequency components of each input signal component are used to regulate a current which is directed along the other respective one of the lines. Thus, the difference in the total currents on the two lines is greater for high frequency components than for low-frequency components.

Specifically, the first aspect of the present invention may be expressed as a data transmission system including:

a pair of electrical transmission lines;

a current source connected to each of said lines;

a transmission regulator which receives data as two opposite input signals, and which transmits the signal along the electrical transmission lines as a difference between the currents along the lines; and

5 means for measuring the difference between the currents along the lines, and from the difference extracting the signal;

wherein the transmission regulator divides each input signal into two components, and for each input signal:

10 modifies the current in a respective first one of the transmission lines using a first component of that input signal component, and

applies a low-pass filter to the other one of the components, and using the output of the low-pass filter modifies the current in the respective other one of the transmission lines;

15 whereby the difference between the currents in the two lines is greater for higher frequency components than for low frequency components.

Preferably, the degree to which the output of each low-pass filter modifies the respective other one of the transmission lines, is variable. This permits the transmission regulator to be tuned according to the frequency characteristics of the transmission lines.

20 The possibility of tuning may be achieved, for example, by selectively feeding the output of the low pass filters to a control input (e.g. gate/base) of a plurality of regulating elements (e.g. transistors) which regulate a current directed through the other one of the transmission lines. Switching elements may be provided to determine which of the regulating elements are selected.
25 Thus, the amplification of the low frequency components may be performed using a selected combination of these regulating elements.

Varying the regulation by controlling whether or not transistors are selected has particular advantages over pre-emphasis using passive components: firstly, the manufacture of transistors can be controlled very
30 accurately, and thus the degree of influence of the low frequency components can be controlled very accurately by controlling which transistors are used (by contrast resistors are often inaccurate); secondly, modern CMOS process targets digit technologies very aggressively, so resistors and capacitors are

not always supported; thirdly, accurate transistor models for simulations are always available, but not capacitors or resistors.

Furthermore, the system according to the present invention can be arranged to ensure that the worst case pulse (e.g. a pulse which is part of a signal profile in which all the rest of the profile has opposite polarity) has a larger amplitude than would be possible by relying on a conventional passive pre-emphasis filter (i.e. there is gain).

Furthermore, the system according to the present invention can be arranged with only a low number of devices in series, so that the system is amenable to low voltage applications (say, signals of only up to 5V, or even only up to 2V).

As pointed out above, the transmission characteristics of a given transmission line are usually unknown. In this case, it is useful to provide a procedure for selecting the combination of regulating elements used, so that the characteristics of the pre-emphasis are matched to the transmission characteristics.

This can be accomplished by initially setting the switches of the regulator so that the influence of the low-pass filtered signals on the current is lowest (i.e the pre-emphasis of the high frequency portions of the signal is lowest); transmitting pulses of known length (e.g. worst case - that is narrowest - pulses); measuring the duration of the received pulse; and gradually modifying the switches to increase the influence of the low-pass filtered signals until the measured duration of the pulse is as great as the transmitted duration (to within a certain tolerance). This concept provides a second, independent aspect of the invention.

Specifically, in the second aspect, the present invention further proposes, in a system which includes a device for differentially amplifying low frequency components and high frequency components in a received signal, and in which the amplified signal is transmitted from a first end of a transmission line to a second end of at least one transmission line, a method of setting the differential amplification of the low frequency and high frequency components, the method including:

repeatedly generating pulses of known duration;

amplifying low frequency components and high frequency components in the generated pulses to different degrees to form a modified pulse;

transmitting the modified pulses along the line from the first end;

measuring the duration of the received pulses received at the second

5 end; and

increasing the degree to which high frequency components are amplified relative to low frequency components until the measured duration of the received pulses is equal to the known duration of the generated pulses to within a predetermined tolerance. The system may comprise means to

10 perform this method automatically, e.g. upon connection to at least one new transmission line.

Preferably, the system in question is one according to the first aspect of the invention.

Brief description of the drawings

15 Non-limiting embodiments of the invention will now be described for the sake of example only with reference to the accompanying drawings in which:

Fig. 1 shows a typical frequency response of a transmission line;

Fig. 2 shows the modification in transmitted data caused by

20 transmission along the transmission line of Fig. 1;

Fig. 3 shows a known CDL driver;

Fig. 4 shows a known pre-emphasis technique;

Fig. 5 shows a first driver according to the invention;

Fig. 6 illustrates the effect of the driver shown in Fig. 5;

25 Fig. 7 shows a second driver according to the invention;

Fig. 8 illustrates a calibration technique according to the invention; and

Fig. 9 illustrates a third driver according to the invention.

Detailed description of embodiments

30 A first embodiment of the invention is illustrated in Fig. 5. In the differential pair for this version of the CML driver, there are, in comparison

with the driver of Fig. 3, two low pass filters 11,13, which each consist of a resistor R and capacitor C , and additional transistors 15,17. The transistors 15, 17 each have a width (which is proportional to gain) W_2 . Each of the two complementary (equal and opposite) input signals are amplified to form equal and opposite signals txp and txn , are these are divided into two signal paths (by components which are not shown). Note that the amplification may alternatively be performed after the signals txp are divided. For each signal, a first signal path leads to a respective transistor 3,5 of width W_1 and controls a current through the transistor which is directed into a respective transmission line 7,9 in the manner described above in relation to Fig. 3; a second signal path passes through one of the low pass filters 11,13 to a respective one of the transistors 15, 17 of width W_2 , which controls another current, which is directed to the respective other one of the transmission lines. In other words, each transmission line carries a current which is the sum of a current passing through a transistor of width W_1 and a current passing through a transistor of width W_2 which is controlled by a low-pass filtered version of the opposite input signal.

Therefore, for a low frequency signal, the gain of the driver (e.g. the signal which is passed to the first transmission line 9 compared to signal txp) is proportional to $W_1 - W_2$ (i.e. width1-width2). At high frequencies, the low pass filters 11,13 mean that no signal is applied to the transistors 15,17, so that the gain of the driver is proportional to W_1 . The width W_1 should be bigger than W_2 , otherwise the correct frequency response will not be achieved, and as W_2 approaches W_1 the maximum difference in the two gains is achieved.

We will now analyse in more detail, and in relation to Fig. 6, the operation of the driver of Fig. 5.

The upper portion of Fig. 6 shows the frequency response of three transmission lines 20, 21, 22. A relatively short interconnect (e.g. with a length of a few cm) has a frequency response shown as 20, which is a plateau up to a relatively high frequency, but above this frequency gradually decreases ("rolls off"). This "roll-off" frequency is above the highest frequency present in

the data marked by the dashed line 23, and so causes no problem. Typically, the frequency 23 is at least 200 MHz or at least 500 MHz, typically more than 1GHz for 10¹¹ of FR4 PCB. Progressively longer transmission lines have frequency responses 21, 22 with progressively lower roll-off frequencies ω_{2A} , ω_{2B} . Frequently, the roll-off frequency of a given transmission line is not
 5 known in advance. For a transmission line with a roll off frequency below the highest data frequency (which in typical high speed modern applications may happen when the transmission line is as short as only a few tens of centimetres), the problems illustrated in Fig. 2 will occur.

Turning to the lower portion of Fig. 6, lines 24,26 show the frequency response for two drivers according to Fig. 5 having the same value of W_1 but different respective values of W_2 , namely W_{2A} and W_{2B} where W_{2B} is closer to W_1 than W_{2A} . At high frequency, the maximum gain for each is W_1 , but the gain of each line 24,26 decreases for frequencies below $\omega_1=1/(2\pi RC)$ and
 15 reaches its lowest value, determined by W_1 and W_2 at a lower frequency. Specifically, the gain of each driver decreases from ω_1 by 20dB/decade as a result of the filters, until it intercepts the minimum gain (W_1-W_2) of the drive. This minimum gain is thus achieved at a frequency (respectively ω_{2A} and ω_{2B}) which depends upon the respective values W_{2A} and W_{2B} .

The gain profile 24 is complementary to the frequency response 21, so that it is suitable for providing pre-emphasis in the manner shown in Fig. 4 for the "long" transmission line. Similarly, the gain profile 26 is complementary to the frequency response 22, so that is particularly suitable for providing pre-emphasis for the "very long" transmission line.

The above discussion demonstrates that the frequency response of a driver according to Fig. 5 can be adjusted (tuned) by altering the width W_2 .

Fig. 7 shows an embodiment of the invention in which such tuning may be achieved without replacement of components. The circuit of Fig. 7 may be thought of as a multiple input differential pair. Each of the transistors 15,17 of
 30 Fig. 5 is replaced with a set of N ($N \geq 2$) transistors (in Fig. 7 $N=3$). The

switches 30 can select any combination of the transistors (corresponding sets of transistors should be selected for each of the signals t_{xp} and t_{xn}). To use the terminology of Fig. 5, the more transistors that are selected the larger the effective total width of W_2 and the lower ω_2 becomes. The N transistors for each of t_{xp} and t_{xn} can be implemented using a binary weighting so that 2^N combinations of settings of W_2 are possible.

The advantages of this approach to pre-emphasis are:

- 1) The use of passive components is reduced to a minimum.
- 2) Matching of pre-emphasis to interconnect is determined by transistor dimensions which are accurately manufactured and modelled.
- 3) It is possible to get gain out of the driver so that the worst case pulse has larger amplitude than would otherwise be possible with a conventional passive pre-emphasis filter.
- 4) This approach is amenable to low voltage operation due to the low number of devices in series.

In our speed applications the low pass filter function may be implemented with capacitors since these are sufficient to load the pre-driver to roll off above the frequencies of interest.

Fig. 8 illustrates the calibration of pre-emphasis. When programmable pre-emphasis is applied to an interconnect of unknown frequency response, or it is desired to fine tune the pre-emphasis to compensate for process variation, a calibration cycle is performed. This adjusts the settings of the filter until its response best cancels that of the interconnect.

The transceivers in which we apply these pre-emphasis techniques have mixers which adjust the phase of the receiver clock in pre-determined phase steps. This technique measures the data width of the worst case pattern using the mixers and is shown in the diagram below. The mixers move the sample point across the data pulse as shown in Fig. 8. Therefore the result is

a logic low, then high, and finally a low again. Pre-emphasis is increased until it takes a known number of phase steps to move the sample point across the data pulse (i.e. the pulse width measurement is correct).

5 A system according to the invention which can perform this method automatically (e.g. when instructed to do so) is shown in Fig. 9. The system for setting the pre-emphasis operates as follows:

Step 1: The transmitter 35 is set with its pre-emphasis at minimum. It receives and re-transmits the worse case pattern (e.g. 13 0s and a 1) as a serial data stream.

10 Step 2: The receiver 36 spins its phase until the 1 is located in a pre-determined location at the parallel data output of the receiver (e.g. bit 0). If the 1 cannot be located then the pre-emphasis at the transmitter 35 is increased until the 1 is located.

15 Step 3: The phase is decremented until the 1 is no longer present in the located bit position using the mixer. This positions the sample point at the start of the bit because it is possible to begin with the 1 initially located in the correct location in step 2.

20 Step 4: The phase is now incremented so that the sample point is swept across the 1 until it is no longer present in the bit location and the number of increments counted.

Step 5: If the number of increments is less than the value for the correct pulse width then calibration control 37 increments the pre-emphasis at the transmitter 35 and the procedure from step 2 is repeated.

25 This procedure does not require any data alignment to be performed which is advantageous since the frequency response of the interconnect could prevent alignment being maintained. Note that the approach takes into account process variation of the filter components and transistor gains since they are included in the measurement procedure. Also, no extra high speed hardware is required but a simple control function would need to be implemented.

Fig. 9 an alternative embodiment of the invention is shown. The pre-driver section of the embodiment includes separate pre-drivers 40, 41 to produce the signals txn, txp which provide the basic transmitted signal (without pre-emphasis) the signals txn_ip, txp_ip which are used to provide the pre-emphasis.

Although the invention has been described above in relation to particular embodiments, many variations are possible within the scope of the invention as will be clear to a skilled person. For example, in some embodiments any or all of the capacitors replaced by transistor circuitry which emulates them.

Claims

1. A data transmission system including:
 - a pair of electrical transmission lines;
 - a current source connected to each of said lines;
 - 5 a transmission regulator which receives data as two opposite input signals, and which transmits the signal along the electrical transmission lines as a difference between the currents along the lines; and
 - means for measuring the difference between the currents along the lines, and from the difference extracting the signal;
 - 10 wherein the transmission regulator divides each input signal into two components, and for each input signal:
 - modifies the current in a respective first one of the transmission lines using a first component of that input signal component, and
 - applies a low-pass filter to the other one of the components, and using
 - 15 the output of the low-pass filter modifies the current in the respective other one of the transmission lines;
 - whereby the difference between the currents in the two lines is greater for higher frequency components than for low frequency components.
2. A system according to claim 1 in which the output of each said low-pass filter is used to control at least one regulator element which regulates a
- 20 current directed into the respective other one of the transmission lines.
3. A system according to claim 2 in which there are a plurality of regulating elements, and switching means which determine which of the regulating elements the output of each said low-pass filter controls.
- 25 4. A system according to claim 2 in which the at least one regulator element is a transistor.
5. A data transmission system comprising two electrical transmission lines, and means for recognising a signal transmitted along the transmission lines from a difference between the currents flowing on the two lines, the
- 30 signal comprising:
 - means for receiving a signal and dividing the signal into two components;

a low-pass filter arranged to perform a low-pass filter operation on one component; and

for each line, means to modify current flowing in the line using a respective one of the components.

- 5 6. A method of calibrating a system which includes a device for differentially amplifying low frequency components and high frequency components in a received signal, and in which the amplified signal is transmitted from a first end of a transmission line to a second end of the transmission line, the method including:

- 10 repeatedly generating pulses of known duration;
amplifying low frequency components and high frequency components in the generated pulses to different degrees to form a modified pulse;
transmitting the modified pulses along the line from the first end;
measuring the duration of the received pulses received at the second
15 end; and

increasing the degree to which high frequency components are amplified relative to low frequency components until the measured duration of the received pulses is equal to the known duration of the generated pulses to within a predetermined tolerance.

Abstract

A driver transmits data as a difference in the currents along two transmission lines. The driver provides a difference in the currents which is greater for relatively high frequency components, by transmitting relatively low frequency components in the data to both of the transmission lines. The degree to which low frequency components are transmitted to one of the lines is dependent upon the width (gain) of a transistor, and thus may be varied by changing the transistor width rather than the value of a passive component. In some versions of the device, the frequency response of the driver can be varied by selecting combinations of transistors to provide this gain. A calibration method allows the variable response to be tuned to properties of the transmission lines.

[Fig. 5]




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7

811




Fig. 9

36 →




Fig. 8




Fig. 9